

AN1261

Use of 32K x 36 FSRAM in Non-parity Applications

Prepared by: Michael Peters, FSRAM Applications Engineer

The MCM69F536 and MCM69P536 are synchronous fast static BurstRAMs™ that are organized as 32K words of 36 bits (or four bytes wide) each. The I/O pins contain byte parity. The JEDEC standard pin assignment for synchronous SRAMs defines the corner I/O pins of the 100 pin QFP/TQFP package as either a parity I/O or as a no connect. A RAM organized as 32 bits wide is achieved by making the corner I/O pins no connect.


Motorola's MCM69F536, MCM69P536, and future x36 BurstRAMs can be used in non-parity applications by simply making one of the following two design choices.

1. Connect pulldown (or pullup to 3.3 V_{VCC}) resistors to V_{SS} on the parity I/O pins. The recommended resistor value should be within the 1 kΩ to 10 kΩ range. This is the recommended design choice.

2. Allow the parity I/O pins to be left open circuit. This is not the recommended design choice. One might experience problems associated with floating I/O pins, such as an increase in I_{CC} current.

In general, the use of pulldown/pullup (strap) resistor values closer to 1 kΩ are preferred, since they provide a lower impedance to ac ground (V_{SS} or V_{CC}) and therefore less susceptible to its neighboring pin's noise. The drawback is slightly increased power consumption. However, this additional power is consumed only during the initial read/write cycles after power-up. The array bit pattern upon power-up will be random, so the resistor straps draw current only during read cycles in which the output drives to the opposite state of the strap voltage. During write cycles, the resistor straps insure the parity bits are written with a binary 0 or 1 dependent upon the strap voltage chosen. Subsequent read cycles will return the same binary value that was previously written by the resistor strap. After the entire 32K memory words have been

written, no additional power is consumed by the SRAM due to the parity strap resistors.



JEDEC Standard Pin Assignment and Parity Bit Resistors Connected to Ground

BurstRAM is a trademark of Motorola, Inc.

3/27/96

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

Mfax is a trademark of Motorola, Inc.

How to reach us:

USA/EUROPE/Locations Not Listed: Motorola Literature Distribution;
P.O. Box 5405, Denver, Colorado 80217. 303-675-2140 or 1-800-441-2447

JAPAN: Nippon Motorola Ltd.: SPD, Strategic Planning Office, 4-32-1,
Nishi-Gotanda, Shinagawa-ku, Tokyo 141, Japan. 81-3-5487-8488

Mfax™: RMFAX0@email.sps.mot.com – TOUCHTONE 602-244-6609
– US & Canada ONLY 1-800-774-1848

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,
51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298

INTERNET: <http://motorola.com/sps>

