

Motorola Semiconductor Engineering Bulletin

EB292

Initialization Considerations When Moving from the BUFFALO Monitor to a Standalone MC68HC11

By Janet M. Snyder
Austin, Texas

General Information

Analog-to-digital (A/D) convertor code written under the BUFFALO monitor oftentimes does not run on a standalone MC68HC11 because of a simple error.

You must initialize the A/D convertor by writing a 1 to the A/D converter power-up bit (ADPU) in the option register. The A/D code executes properly under the BUFFALO monitor because BUFFALO initializes the A/D converter as part of its reset initialization sequence. The initialization of the A/D is found in the BUFFALO source code as the first two lines of the BUFISIT routine (lines 164 and 165) in the *M68HC11EVBU User's Manual*, Motorola document order number MC68HC11EVBU/AD2.

BUFFALO initializes other things that may have been overlooked in your code. The BUFFALO monitor programs the OPTION register like this:

- Oscillator startup delay is enabled (DLY = 1).
- The COP timer rate to a divide by 64 (CR1:CR = %11).
- IRQ is set for low-level sensitivity (IRQE = 0).
- The clock monitor is disabled (CME = 0).




- The A/D is set to use the system E clock (CSEL =0).

The BUFFALO monitor also provides these initial settings:

- The BPROT register is cleared, enabling writes to EEPROM and the CONFIG register.
- The stack pointer is initialized.

The bottom line is that whenever code runs successfully under the BUFFALO monitor and fails on a standalone MC68HC11, the problem is generally something that is not being initialized in the standalone code that was initialized automatically under BUFFALO.

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:

USA/EUROPE/Locations Not Listed: Motorola Literature Distribution, P.O. Box 5405, Denver, Colorado 80217, 1-800-441-2447 or 1-303-675-2140. Customer Focus Center, 1-800-521-6274

JAPAN: Nippon Motorola Ltd.: SPD, Strategic Planning Office, 141, 4-32-1 Nishi-Gotanda, Shinigawa-Ku, Tokyo, Japan. 03-5487-8488

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd., 8B Tai Ping Industrial Park, 51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298

Mfax™, Motorola Fax Back System: RMFAX0@email.sps.mot.com; <http://sps.motorola.com/mfax/>;

TOUCHTONE, 1-602-244-6609; US and Canada ONLY, 1-800-774-1848

HOME PAGE: <http://motorola.com/sps/>

Mfax is a trademark of Motorola, Inc.



MOTOROLA

© Motorola, Inc., 1998

EB292/D