

## *Mask Set Errata 2*

# **68HC705JP7 8-Bit Microcontroller Unit**

---

---

## **INTRODUCTION**

This mask set errata provides information regarding the analog subsystem, high-current output of port C and port B bit 4, low voltage reset, and the sample and hold capacitor leakage discharge rate of these MC68HC705JP7 MCU mask set devices:

- 0H70H
- 1H70H

---

---

## **MCU DEVICE MASK SET IDENTIFICATION**

The mask set is identified by a 5-character code consisting of a version number, a letter, two numerical digits, and a letter, for example 0H70H. Slight variations to the mask set identification code may result in an altered version number, for example 1H70H.

---

---

## **MCU DEVICE DATE CODES**

Device markings indicate the week of manufacture and the mask set used. The data is coded as four numerical digits where the first two digits indicate the year and the last two digits indicate the work week. For instance, the date code "9115" indicates the 15th week of the year 1991.

---

---

## **MCU DEVICE PART NUMBER PREFIXES**

Some MCU samples and devices are marked with an SC or XC prefix. An SC prefix denotes special/custom device. An XC prefix denotes that the device is tested but is not fully characterized or qualified over the full range of normal manufacturing process variations. After full characterization and qualification, devices will be marked with the MC prefix.

*Whenever contacting a Motorola representative for assistance, please have the MCU device mask set and date code information available.*

Specifications and information herein are subject to change without notice.



## ANALOG SUBSYSTEM

---

---

The minimum analog subsystem discharge device value is 0.5 mA.

The temperature diode does not meet the temperature change in the voltage specification.

These analog subsystem characteristics, which are ordinarily selectable after setting the OPT bit, are not yet available:

- Output of comparator 1 on port B bit 4  
The COE1 bit is not writable. Reading it returns a logical 0.
- Ground offset voltage applied to sample capacitor  
The VOFF bit is not writable. Reading it returns a logical 0.

## HIGH-CURRENT OUTPUT OF PORT C AND PB4

---

---

Port C and PB4 do not yet have high-current output capabilities. Port C and port B perform to the standard  $V_{OL}$  and  $V_{OH}$  specifications mentioned for Port B. At this time, only port A has high-current output capabilities.

## LOW VOLTAGE RESET (LVR) TRIP POINT AND HYSTERESIS

---

---

The LVR does not meet the minimum trip point specifications. The actual trip point may be lower than the minimum operating voltage of the CPU. Therefore, proper CPU operation down to the LVR trip point cannot be guaranteed.

The LVR also does not meet the minimum hysteresis specification.

## SAMPLE CAPACITOR LEAKAGE DISCHARGE RATE

---

---

The leakage discharge rate of the internal sample and hold capacitor may not meet the specification of 0.2 V/sec at  $V_{DD} = 5\text{ V}$  or 0.1 V/sec at  $V_{DD} = 3\text{ V}$ . Actual leakage rate varies with operating method, temperature, and external grounding.

### How to reach us:

**USA/EUROPE/Locations Not Listed:** Motorola Literature Distribution, P.O. Box 5405, Denver, Colorado 80217, 1-800-441-2447 or 1-303-675-2140. Customer Focus Center, 1-800-521-6274

**JAPAN:** Nippon Motorola Ltd. SPD, Strategic Planning Office 4-32-1, Nishi-Gotanda Shinagawa-ku, Tokyo 141, Japan, 81-3-5487-8488


**ASIA/PACIFIC:** Motorola Semiconductors H.K. Ltd., 8B Tai Ping Industrial Park, 51 Ting Kok Road, Tai Po, N.T., Hong Kong, 852-26629298

**Mfax™, Motorola Fax Back System:** RMFAX0@email.sps.mot.com; <http://sps.motorola.com/mfax/>;

TOUCHTONE, 1-602-244-6609; US and Canada ONLY, 1-800-774-1848

**HOME PAGE:** <http://motorola.com/sps/>

Mfax is a trademark of Motorola, Inc.

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

Additional mask set erratas can be found on the World Wide Web at <http://Design-NET.com/csic/TECHSPRT/TechSprt.htm>.



**MOTOROLA**

68HC705JP7MSE2