

AN1552

MPX7100AP: The Sensor at the Heart of Solid-State Altimeter Applications

By Chris Winkler and Jeff Baum
Sensor Systems Engineering Group
Motorola Semiconductor Products Sector
Phoenix, Arizona

INTRODUCTION

The advent of piezoresistive, bulk micromachined silicon pressure sensing devices has revolutionized sensor technology. These sensors have significantly lowered system costs and opened doors to sensing solutions never before considered possible. In addition, the integration of on-chip temperature compensation, calibration, and signal-conditioning circuitry (resulting in a microprocessor-compatible output) onto a single monolithic sensing device has eliminated many of the cost and reliability issues encountered with systems incorporating electromechanical sensors. Now, add these developments to the decreasing cost of microcontrollers (MCU) for embedded control systems, and the sensing solution possibilities seem endless. This document outlines a system approach that is designed to measure and display altitude over a specified range. Although this system can be implemented equally well with an MPX2100AP, we have chosen to design our system around the low-power version of the MPX2100AP—the MPX7100AP. There are many altimeter

applications where it is desirable to run the electronic system from battery power. In such cases, the MPX7100AP has an additional benefit—it has an input impedance that is approximately five times greater than its MPX2000 series counterpart. Thus, the power consumption will be five times less than that of the MPX2100AP.

The system presented here demonstrates how the Motorola MPX7100AP (100 kPa absolute ported high-impedance) pressure transducer may be utilized for altimeter applications. This simple design serves as a building block from which more sophisticated systems can be developed. Additional circuitry, software routines, and higher precision component selection can allow for increased accuracy, additional resolution, and a variety of altimeter system features (including variometers, travel memory, audio warning signals, barographs, and maximum/minimum tracking). Table 1 is a representation of the system in terms of its general operating specifications.

Table 1. General System Specifications

Display Units	Altitude in ft.
Resolution (Maximum)	80 ft.
Temperature Range	-10 to 40°C
Altitude Range	0 - 9999 ft.

ALTITUDE MEASUREMENT

An altimeter is a device that converts absolute atmospheric pressure measurements into an altitude approximation. This absolute pressure is typically measured with respect to absolute zero pressure (i.e., a vacuum-sealed reference). Atmospheric pressure is inversely related to altitude; therefore, lower atmospheric pressure is encountered at higher altitudes. However, the pressure at a particular altitude fluctuates significantly as a result of changing weather conditions. Consequently, a calibration scheme must be frequently employed to control the accuracy of the approximation.

For these reasons, the most crucial device in this system is the silicon pressure sensor. This device produces an analog voltage signal (mV range) for an applied atmospheric pressure. The pressure corresponding to the sensor output signal

is mathematically converted into altitude via a microcontroller. The pressure transducer used in this system is sensitive enough to detect pressure variations corresponding to altitude changes of one foot. Since the sensor output signal is typically less than 50 mV, it must be amplified and signal-conditioned for proper interfacing to a microcontroller.

The system resolution is determined by the resolution of the analog-to-digital (A/D) converter. The overall accuracy is governed by the transducer accuracy, the nonlinear relationship between pressure and altitude, and the signal-conditioning circuitry. Hence, there are independent factors that determine system accuracy and resolution. Accuracy, resolution, and range cannot be optimized simultaneously. The design presented here is intended to display altitudes of up to 9,999 feet accurately, with a maximum resolution of 80 feet.

AN1552

For discussion purposes, the standardized absolute atmospheric pressure at sea level is designated as 29.92 inches of mercury (” Hg). The use of a standard pressure scale allows for reference between pressure and altitude under normalized climate conditions at a particular altitude. This standardized pressure decreases to 20.57” Hg at an altitude of approximately 10,000 feet. As mentioned before, the atmospheric

pressure can differ by ± 1 ” Hg due to climate changes. The standard pressures at several altitudes are displayed in Table 2. Over the intended operating altitude range, the absolute atmospheric pressure is expected to fluctuate from approximately 30.5” Hg to a minimum of 20” Hg. This information is critical to the overall design.

Table 2. Altitude vs. Pressure Data

Altitude, ft.	Pressure, ” Hg
0	29.92
500	29.38
1,000	28.85
6,000	23.97
10,000	20.57
15,000	16.86

DESIGN OVERVIEW

The remaining sections of this text describe the system design. The design is separated into subsystems as depicted in Figure 1. Each module accomplishes a specific task critical to the altitude translation process. The encountered atmospheric pressure is first converted into a differential voltage signal. This signal is then conditioned for compatibility with the

analog-to-digital converter inputs of the microcontroller. A digital representation of this analog signal is mathematically converted into a pressure measurement. The microcontroller then implements a “look-up” procedure to convert this measurement into a corresponding altitude approximation. Finally, the appropriate data is transmitted serially to the LCD interface to display the altitude in feet. A discussion of each subsystem details the important design considerations.




Figure 1. Altimeter Block Diagram

PRESSURE SENSOR

The most critical element of this design is the pressure transducer. This device typically produces a differential output voltage linearly proportional to an applied pressure. The linearity and temperature stability of the sensor output signal over the intended operating conditions must not introduce significant errors. Otherwise, additional circuitry or software algorithms must be incorporated to compensate for the error created by the sensor. As indicated in the background information provided earlier, the output signal of the sensor must have a linear response function over the expected pressure range of 20–30.5" Hg. Therefore, the required full-scale pressure rating for this device is approximately 30" Hg (100 kPa). In order to measure absolute atmospheric pressure variations, the device must measure applied pressures with respect to a known, fixed pressure reference. Absolute zero (vacuum) is the easiest fixed reference to provide, with respect to manufacturability, and exhibits the best stability over temperature variations.

Based on these criteria, the design employs a Motorola MPX7100AP silicon pressure transducer. The MPX7000 series pressure transducers include on-chip temperature compensation and calibration circuitry. The zero-pressure offset voltage and full-scale span are trimmed to specified tolerances. These devices are available in full-scale pressure ranges from 10 kPa (1.5 PSI) to 700 kPa (100 PSI). To allow for use in different applications, the sensors are available in several configurations (gauge, differential, and absolute sensing) along with a variety of packaging/porting options. The MPX7100AP is an absolute sensing device that is designed to measure pressure applied to a single port with respect to absolute zero pressure sealed in an evacuated reference cavity. This feature of the transducer is critical to the design, as absolute barometric pressure must be measured with reference to a fixed pressure that is immune to ambient pressure fluctuations. The electrical characteristics for this device are summarized in Table 3. As suggested in the introduction, the MPX2100AP can provide the same functionality as the MPX7100AP. The major parametric difference between devices is that the MPX7100 is better suited for portable applications, as a result of its five times greater input resistance.

The sensor supply voltage can be varied as indicated in Table 3. The full-scale output signal, nominally rated at 40 mV

for a supply voltage of 10 Vdc, is linearly proportional to the sensor supply voltage. In this system, all nondigital circuit elements are operated with an 8-Vdc regulated supply. At this supply voltage, the sensor will produce a differential output signal of 32 mV at the full-scale pressure of 100 kPa.

Zero-pressure offset and full-scale span variations for this device are trimmed to the tolerances shown in Table 3. To simplify the design, no additional circuitry or software is included to compensate or calibrate the sensor output signal beyond the tolerances shown. The combined effects of temperature variations and nonlinearity introduce a maximum error of 4% into the sensor output signal. Considering the linear response of the sensor and the operating pressure range, the sensor output signal is calculated to change from 32 mV to 16.2 mV over the entire altitude range. These nominal values are subject to the tolerances previously discussed.

SIGNAL-CONDITIONING CIRCUITRY

The low-level differential output signal of the pressure sensor must be amplified to an analog voltage level compatible with the A/D inputs of the microcontroller. An instrumentation amplifier circuit converts the sensor output to a ground-referenced, 0.5 to 4.5 Vdc analog voltage. The dual operational amplifier circuit shown in Figure 2 provides the amplification, level-shifting, and stability to produce the desired analog signal. The MC33272 dual operational amplifier IC provides high output stability, low input offset voltage, low offset voltage thermal drift, and single-ended supply capability at low cost. An 8-volt regulator (MC78L08ACP) is included to limit supply voltage variations that can affect the accuracy of the circuit output.

This circuit will invert, amplify, and level-shift the differential input signal (difference between S⁺ and S⁻ sensor outputs). The transfer function for this circuit will have a linearly decreasing output for increasing differential input. Consequently, as altitude increases, the circuit output voltage will increase. This feature simplifies the mathematical processing in the software and eliminates the need for a negative supply voltage to provide the necessary level-shift of the amplified offset pedestal reference. The offset voltage is trimmable through resistor R_{Offset1} to obtain a 0.5-V output at sea level. This feature allows for system calibration at a known altitude reference.

Table 3. MPX7100AP Operating Characteristics
(Supply Voltage = 10 Vdc, TA=25°C unless otherwise noted)

Characteristic	Symbol	Min	Typical	Max	Unit
Pressure Range	P _{OP}	0	–	100	kPa
Supply Voltage	V _S	–	10	16	Vdc
Supply Current	I _o	–	1.0	–	mAdc
Full-Scale Span	V _{FSS}	38.5	40	41.5	mV
Zero-Pressure Offset	V _{off}	–2.0	–	2.0	mV
Sensitivity	ΔV/ΔP	–	0.4	–	mV/kPa
Linearity	–	–1.0	–	1.0	%V _{FSS}
Temperature Effect on Span	TCV _{FSS}	–1.0	–	1.0	%V _{FSS}
Temperature Effect on Offset	TCV _{off}	–1.0	–	1.0	mV




Figure 2. Signal-Conditioning Circuit

Using the transfer function for this circuit, the offset voltage and gain can be determined to provide maximum resolution and the desired output voltage. The calculation of these parameters for this circuit is illustrated as follows:

In determining the amplifier gain, the maximum offset voltage across $R_{offset2}$ is selected as approximately 7.0 Vdc. This value allows some room for adjustment and maximum signal gain. The amplified sensor signal at sea level cannot contribute more than the theoretical value of -6.5 Vdc, while allowing for the desired circuit output of 0.5 V.

Sensor Output at Sea Level (30.5" Hg) \approx 32.4 mV
 Required Gain = $-6.5 \text{ V} / 32.4 \text{ mV} \approx -201$
 Sensor Output at 9,999 ft. (20.5" Hg) \approx 22.2 mV
 Amplifier Output = $(22.2 \text{ mV} \times -201) + 7.0 \text{ V} = 2.53 \text{ V}$

The span voltage is approximately 2.0 V. The 8-bit (255 steps) resolution provided by the A/D converter on-board the MCU will detect 19.6 mV of change per step. The number of steps used in this process is determinable.

$$VRH = 5.0 \text{ V}, VRL = 0.0 \text{ V}$$

therefore, $5.0 \text{ V} / 255 \text{ steps} \approx 19.6 \text{ mV/step}$

$$\text{Steps Required} = 2.0 \text{ V} / 19.6 \text{ mV} = 104 \text{ steps}$$

The calculated gain is then used to determine the appropriate resistor values for the amplifier circuit defined by the transfer function shown in the following. The values for the offset resistors were selected to trim the offset voltage over the range of 8.0 – 6.6 Vdc.

$$V_{out} = - [R2/R1 + 1] \times V_{diff} + V_{off}, V_{diff} = 32.4 \text{ mV}$$

$$R1 \approx R3 = 100 \Omega, R2 \approx R4 = 20 \text{ k}\Omega$$

Using 1% tolerance resistors, a common mode rejection ratio (CMRR) of approximately 75 dB can be obtained. The potentiometer is used to vary the offset voltage and allow for frequent calibration of the system as required to track the effects of changing weather conditions at a reference altitude.

MICROCONTROLLER INTERFACE

Embedded microcontrollers are extremely useful devices in data acquisition systems. The decreasing costs have made widespread use feasible. The microcontroller employed in this system, the Motorola MC68HC11, is representative of a state-of-the-art 8-bit MCU. The MC68HC11 incorporates an 8-channel A/D with 8-bit resolution, a 16-bit enhanced timer (including a COP watchdog), an SPI (Serial Peripheral Interface: Synchronous), an SCI (Serial Communications Interface: Asynchronous), and a maximum of 40 parallel I/O lines. The HC11 is available in several package configurations and product variations allowing for additional RAM, EEPROM, and

I/O capability. The software was developed using the M68HC11EVB development system. This evaluation system is driven by the BUFFALO monitor program that can be operated from a host computer to develop and debug code.

In developing the system code, the following processing flow was used to outline the steps necessary for the conversion process. The system will convert the analog voltage into an 8-bit digital approximation, convert the pressure variation into altitude, and output this value to an LCD display interface serially (through the on-board SPI). Following is an outline of the process in greater detail:

1. Initialize and enable the A/D converter, SPI interface.
2. Initialize memory locations. Initialize variables.
3. Make A/D conversion of amplified sensor output. Store result.
4. "Look-Up" to determine altitude from pressure measurement.
5. Determine if conversion is in system range.
6. Convert pressure into decimal display digits or error message.
7. Output result via SPI to LCD interface.

The system is designed to display an error message if the conversion is out of the specified operating altitude range (0–9,999 ft.) A "hi" is displayed if the conversion result is

above 9,999 feet, and a "lo" is displayed for a conversion below sea level. A listing of the assembly source code to implement these tasks is included in the Appendix. The altitude "look-up" table was generated using a mathematical function which models the relationship between altitude and barometric pressure. The signal-conditioned sensor output signal is connected to pin PE5 (Port E–A/D Input pin). The HC11 communicates to the LCD display interface via the SPI synchronous clock signal SCLK and the serial data line MOSI (Master Out / Slave In).

LCD DISPLAY INTERFACE

To display the altitude digitally in feet, a serial LCD interface was used to receive data from the HC11. The devices required are an MC145453 CMOS serial interface/LCD driver, and an FE202 four-digit LCD. To display the four decimal digits correctly, the HC11 serially transmits six bytes for each conversion. This includes a start byte, a byte for each of the four decimal display digits, and a stop byte. These decimal digits are used to transmit the numbers 0–9,999. The control of display digits and data transmission is executed in the source code through subroutines BCD_CONV, LOOKUP, SPI2LCD, and TRANSFER. A block diagram of this interface is included in Figure 3.




Figure 3. LCD Display Interface Diagram

CONCLUSION

Silicon pressure sensors can provide the reliability and accuracy required in many applications at a relatively low cost. The altimeter design reviewed in this article is indicative of the system simplification achieved. Having outlined a simplified means of measuring altitude and the design issues involved, more sophisticated systems incorporating additional software and circuitry into this basic design are possible. The MPX7100AP, compensated and calibrated pressure sensor,

is well suited for achieving the desired accuracy and design simplicity for common altimeter applications. Besides the integration of laser-trimmed resistive networks to tighten the device parameter tolerances, the MPX7100AP also offers the power-reducing advantage of low current-drain (due to its high input resistance). These features, combined with the absolute pressure reference sealed within the device's micro-machined cavity, make the MPX7100AP an ideal choice for developing low-power, low-cost altimeter systems.

APPENDIX

Altimeter Software Listing

*ALTIMETER APPLICATIONS PROJECT - Chris Winkler
 *Developed: October 1, 1992 - Motorola Discrete Applications
 *This code is used to implement an MC68HC11 Micro-Controller
 *as master processing unit for a simple Altimeter system.
 *The HC11 will interface with an MPX7100AP to monitor, store,
 *and display measured altitude via the 8-bit A/D channel
 *The sensor output (32 mV max) will be amplified to 0.5 - 2.5 V dc
 *The HC11 will interface with a 4-digit LCD (FE202) via
 *a Motorola LCD driver (MCL145453) to display the 4-digit
 *altitude through the SPI.

*A/D & CPU Register Assignment
 *This code will use index addressing to access the
 *important control registers. All addressing will be
 *indexed off of REGBASE, the base address for these registers.

REGBASE	EQU	\$1000	* register base assignment of control register
ADCTL	EQU	\$30	* offset of A/D conversion control register
ADR2	EQU	\$32	* offset of A/D results register
ADOPT	EQU	\$39	* offset for A/D option register location
PORTB	EQU	\$04	* Location of PORTB used for conversion
PORTD	EQU	\$08	* PORTD Data Register Index
DDRD	EQU	\$09	* offset of Data Direction Reg.
SPCR	EQU	\$28	* offset of SPI Control Reg.
SPSR	EQU	\$29	* offset of SPI Status Reg.
SPDR	EQU	\$2A	* offset of SPI Data Reg.

*User Variables
 *The following locations are used to store important measurements
 *and calculations used in determining the altitude. They
 *are located in the lower 256 bytes of user RAM

DIGIT1	EQU	\$0001	* BCD thousands digit for altitude
DIGIT2	EQU	\$0002	* BCD hundreds digit for altitude
DIGIT3	EQU	\$0003	* BCD tens digit for altitude
DIGIT4	EQU	\$0004	* BCD ones digit for altitude
COUNTER	EQU	\$0005	* Variable to send 5 dummy bytes
ZEROALT	EQU	\$0010	* Storage for 0 altitude in hex
MAXALT	EQU	\$0011	* Storage for system's maximum altitude
PRESSURE	EQU	\$0012	* Storage location for A/D conversion
DELTA_P	EQU	\$0014	* Storage of pressure change in hex format
INDEX	EQU	\$0016	* Index to retrieve entire word from table
ALTITUDE	EQU	\$0018	* Storage of altitude in hex format
FLAG	EQU	\$0020	* Determination of conversion within range

*MAIN PROGRAM

*The conversion process involves the following steps:

*			
*1.	Set-Up SPI device		SPI_CNFG
*2.	Set-Up A/D, Constants		SET_UP
*3.	Delay conversion to LCD		DELAY
*4.	Read A/D, detect error		ADCONV
*5.	Error detected - Code		ERROR
*6.	No Error - Convert Altitude		ALT_CONV
*7.	Convert hex to BCD format		BCDCONV
*8.	Convert LCD display digits		LOOKUP
*9.	Output via SPI to LCD		SPI2LCD

*This process is continually repeated as the loop CONVERT
 *runs unconditionally through BRA (the BRANCH ALWAYS statement)

ORG	\$C000		* DESIGNATES START OF MEMORY MAP FOR USER CODE
	LDX	#REGBASE	* Location of base register for indirect adr
	BSR	SPI_CNFG	* Set-up SPI Module for data X-mit to LCD
	BSR	SET_UP	* Power-Up A/D, initialize constants
CONVERT	BSR	DELAY	* Slow down conversion process for display
	BSR	ADCONV	* Calls subroutine to make A/D conversion
	LDAB	FLAG	* Determines if a range Error has occurred
	CMPB	#\$80	* If No Error detected (FLAG=\$80) then
	BEQ	INRANGE	* system will continue conversion process
	BSR	ERROR	* Upon detecting Error, branches to ERROR
	BRA	OUTPUT	* Branches to output ERROR code

AN1552

*Continues conversion if pressure is in system's range

```
INRANGE    JSR      ALT_CONV    * Convert pressure to altitude in hex
           JSR      BCDCONV    * Converts Hex Result to BCD
           JSR      LOOKUP     * Uses Look-Up Table for BCD-Decimal
OUTPUT     JSR      SPI2LCD    * Output transmission to LCD
           BRA      CONVERT    * Continually converts using Branch Always
```

*Subroutine SPI_CNFG

*Purpose is to initialize SPI, LCD interface for transmission

```
SPI_CNFG   BSET     PORTD,X #20  * Set SPI SS Line High to prevent glitch
           LDAA    #38         * Initializing Data Direction for Port D
           STAA    DDRD,X     * Selecting SS, MOSI, SCK as outputs only
           LDAA    #5D         * Initialize SPI-Control Register
           STAA    SPCR,X     * selecting SPE,MSTR,CPOL,CPHA,CPRO
           LDAA    #5         * sets counter to X-mit 5 blank bytes
           STAA    COUNTER
           LDAA    SPSR,X     * Must read SPSR to clear SPIF Flag
           CLRA
ERASELCD   JSR      TRANSFER   * Calls subroutine to transmit
           DEC     COUNTER
           BNE     ERASELCD
           RTS
```

*Subroutine SET_UP

*Purpose is to initialize constants and to power-up A/D

*and initialize pressures for min. and max. altitudes.

```
SET_UP     LDAA    #90         * selects ADPU bit in OPTION register
           STAA    ADOPT,X    * Power-Up of A/D complete
           LDAB    #0019      * Initialize Hex value of sea level
           STAB    ZEROALT    * Pressure (altitude = 0)
           LDAB    #7D         * Initialize Hex value of highest altitude
           STAB    MAXALT     * Pressure (altitude>9999ft)
           RTS
```

*Subroutine Delay

*Purpose is to delay the conversion process to minimize LCD flickering.

```
DELAY      LDA     #FF        * Loop for delay of display
OUTLOOP    LDB     #FF        * Delay = clk/255*255
INLOOP     DECB
           BNE     INLOOP
           DECA
           BNE     OUTLOOP
           RTS
```

*Subroutine ADCONV

*Purpose is to implement A/D conversion, store the value

*as PRESSURE, and return a value for FLAG to determine

*if this measurement is above or below the system's range.

```
ADCONV     LDX     #REGBASE   * Loads base register for indirect addressing
           LDAA    #25
           STAA    ADCTL,X    * Initializes A/D Conv. Reg.SCAN=1,MULT=0
WTCONV     BRCLR  ADCTL,X #80 WTCONV * Wait for completion of conversion flag
           LDAB    ADR2,X     * Loads conversion result into Accumulator
           STAB    PRESSURE   * Stores A/D conversion as PRESSURE
           STAB    PORTB,X    * Aids in DEBUGGING purposes
```

*The purpose of the following code is to determine if the measurement

*is out of the range of the systems range. The following logical

*statements will set FLAG to a particular value so that the main

*program can determine if the pressure applied is out of range.

*If the pressure is measured as below sea level, FLAG=\$00

*If the pressure is measured as above 9999 ft, FLAG=\$FF

*Otherwise flag is set to an inordinate value, FLAG=\$80

```
           CMPB    ZEROALT    * Determines if conversion<sea level
           BLO     TOLOW     * Branches to set FLAG=$00
           CMPB    MAXALT    * Determines if conversion>9999 ft
           BHI     TOHIGH    * Branches to set FLAG=$FF

           LDAB    #80         * Otherwise conversion is in range
           STAB    FLAG       * Set flag untrue FLAG=$80
           BRA     END_AD     * replaces GOTO RTS
```



```

TOLOW      LDAB      #$00      * Conversion out of lower range
           STAB      FLAG      * FLAG = $00
           BRA       END_AD

TOHIGH     LDAB      #$FF      * Conversion out of upper range
           STAB      FLAG      * FLAG = $FF
END_AD     RTS

*Subroutine ERROR
*This subroutine sets the display digits to output
*an error message having detected an out of range
*measurement in the main program from FLAG

ERROR      LDAB      #$00      * Initialize digits 1,4 to blanks
           STAB      DIGIT1
           STAB      DIGIT4

           LDAB      FLAG      * FLAG is used to determine
           CMPB     #$00      * if above or below range.
           BNE     SET_HI     * If above range GOTO SET_HI

           LDAB      #$0E      * ELSE display LO on display
           STAB      DIGIT2     * Set DIGIT2=L,DIGIT3=0
           LDAB      #$7E
           STAB      DIGIT3
           BRA       END_ERR     * GOTO exit of subroutine

SET_HI     LDAB      #$37      * Set DIGIT2=H,DIGIT3=1
           STAB      DIGIT2
           LDAB      #$30
           STAB      DIGIT3

END_ERR    RTS

*Subroutine ALT_CONV
*Purpose is to determine the pressure variation
*from the calibrated Sea Level pressure - ZEROALT
*The pressure variation,DELTA_P is then used
*as index of ALT_TABLE to look-up the altitude.

ALT_CONV   LDAB      PRESSURE   * Loads A/D sample of pressure
           SUBB     ZEROALT     * DELTA_P = PRESSURE - ALTZERO
           STAB     DELTA_P     * Stores hex result - pressure variation
           LDAA     #$02        * Altitudes are in word format
           MUL      B=DELTA_P by 2 (A) = INDEX
           STD      INDEX      * Allows for correct retrieval of entire word
           LDD      #ALT_TABLE * Loads base of table
           ADDD     INDEX      * Adds INDEX to table base
           STD      INDEX      * INDEX acts as pointer for altitude
           LDY      INDEX      * loads correct location into Y-pointer
           LDD      0,Y        * uses index addr.to look-up altitude
           STD      ALTITUDE   * stores hex format of altitude into memory
           RTS

*Subroutine BCDCONV
*Purpose is to convert ALTITUDE from hex to BCD
*uses standard HEX-BCD conversion scheme
*Divide HEX/10 store Remainder, swap Q & R, repeat
*process until remainder = 0.

BCDCONV   LDAA     #$00        * Default Digits 1,2,3,4 to blanks
           STAA     DIGIT1
           STAA     DIGIT2
           STAA     DIGIT3
           STAA     DIGIT4
           LDY      #DIGIT4    * Conversion starts with lowest digit
           LDD      ALTITUDE   * Load HEX ALTITUDE to be converted
CONVLP    LDX      #$A         * Divide hex digit by 10
           IDIV     X           * Quotient in X, Remainder in D
           STAB     0,Y        * stores 8 LSB's of remainder as BCD digit
           DEY
           CPX      #$0        * Determines if last digit stored
           XGDX
           BNE     CONVLP     * Exchanges remainder & quotient
           LDX      #REGBASE   * returns if Quotient>0
           RTS                * Reloads BASE into main program

```

AN1552

*Subroutine LOOKUP

*Purpose is to implement a Look-Up conversion

*The BCD is used to implement off of TABLE

*where the appropriate hex code to display

*that digit is contained.

*DIGIT4,3,2 are converted only

```
LOOKUP      LDX      #DIGIT1+4    * Counter starts at 5
TABLOOP     DEX
            LDY      #LCDSEGS    * Start with Digit4
            LDAB     0,X         * Loads table base into Y-pointer
            ABY      * Loads current digit into B
            LDAA     0,Y         * Adds to base to index off TABLE
            STAA    0,X         * Stores HEX segment result in A
            CPX      #DIGIT1    * Loop condition complete, DIGIT1 Converted
            BNE     TABLOOP
            RTS
```

*Subroutine SPI2LCD

*Purpose is to output digits to LCD via SPI

*The format for this is to send a start byte,

*four digits, and a stop byte. This system

*will display 4 decimal digits or error code.

*Sending LCD Start Byte

```
SPI2LCD     LDX      #REGBASE
            LDAA     SPSR,X      * Reads to clear SPIF flag
            LDAA     #$02       * 6 0's, no colon, set start bit
            BSR      TRANSFER    * Transmit byte
```

*Sending four decimal digits

```
DLOOP       LDY      #DIGIT1    * Pointer set to send 4 bytes
            LDAA     0,Y         * Loads digit to be x-mitted
            BSR      TRANSFER    * Transmit byte
            INY      * Branch until 4 BYTES sent
            CPY      #DIGIT4+1
            BNE     DLOOP
```

*Sending LCD Stop Byte

```
            LDAA     #$00       * end byte requires all 0's
            BSR      TRANSFER    * Transmit byte
            RTS
```

*Subroutine TRANSFER

*Purpose is to send data bits to SPI

*and wait for conversion complete flag bit to be set.

```
TRANSFER    LDX      #REGBASE
            BCLR     PORTD,X #20 * Assert SS Line to start X-mission
            STAA    SPDR,X      * Load Data into Data Reg.,X-mit
XMIT        BRCLR   SPSR,X #80 XMIT * Wait for flag
            BSET     PORTD,X #20 * DISASSERT SS Line
            LDAB    SPSR,X      * Read to Clear SPI Flag
            RTS
```

*Location for FCB memory for decimal conversion look-up table

*NOTE: 11 possible digits: blank, 0 - 9

```
LCDSEGS     FCB      $7E,$30,$6D,$79,$33,$5B,$5F,$70,$7F,$73,$00
```


*Location for FDB memory for altitude conversion look-up table
*Generated using Approximation Curve calculations simulated
*in EXCEL spreadsheet.

ALT_TABLE	FDB	0000
	FDB	0083
	FDB	0166
	FDB	0250
	FDB	0333
	FDB	0417
	FDB	0501
	FDB	0586
	FDB	0670
	FDB	0755
	FDB	0840
	FDB	0925
	FDB	1010
	FDB	1096
	FDB	1182
	FDB	1268
	FDB	1354
	FDB	1440
	FDB	1527
	FDB	1614
	FDB	1701
	FDB	1788
	FDB	1876
	FDB	1963
	FDB	2051
	FDB	2140
	FDB	2228
	FDB	2317
	FDB	2406
	FDB	2495
	FDB	2584
	FDB	2674
	FDB	2764
	FDB	2854
	FDB	2944
	FDB	3035
	FDB	3126
	FDB	3217
	FDB	3308
	FDB	3400
	FDB	3492
	FDB	3584
	FDB	3676
	FDB	3769
	FDB	3862
	FDB	3955
	FDB	4049
	FDB	4142
	FDB	4236
	FDB	4330
	FDB	4425
	FDB	4520
	FDB	4615
	FDB	4710
	FDB	4806
	FDB	4901
	FDB	4998
	FDB	5094
	FDB	5191
	FDB	5288
	FDB	5385
	FDB	5483
	FDB	5580
	FDB	5679
	FDB	5777
	FDB	5876
	FDB	5975
	FDB	6074
	FDB	6174
	FDB	6274
	FDB	6374
	FDB	6474
	FDB	6575
	FDB	6677

AN1552

FDB	6778
FDB	6880
FDB	6982
FDB	7084
FDB	7187
FDB	7290
FDB	7394
FDB	7498
FDB	7602
FDB	7706
FDB	7811
FDB	7916
FDB	8022
FDB	8127
FDB	8233
FDB	8340
FDB	8447
FDB	8554
FDB	8662
FDB	8770
FDB	8878
FDB	8987
FDB	9096
FDB	9205
FDB	9315
FDB	9425
FDB	9536

END

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters can and do vary in different applications. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:

USA / EUROPE: Motorola Literature Distribution;
P.O. Box 20912; Phoenix, Arizona 85036. 1-800-441-2447

JAPAN: Nippon Motorola Ltd.; Tatsumi-SPD-JLDC, Toshikatsu Otsuki,
6F Seibu-Butsuryu-Center, 3-14-2 Tatsumi Koto-Ku, Tokyo 135, Japan. 03-3521-8315

MFAX: RMFAX0@email.sps.mot.com - TOUCHTONE (602) 244-6609
INTERNET: <http://Design-NET.com>

HONG KONG: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,
51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298



AN1552/D

